

Hot at All Times
Power Distribution Schematics in Wiring Systems
A7
B7
HDLP MOT LH Fuse 4 10 A
A6
B6
HDLP MOT RH Fuse 3 10 A
Fuse Block – Underhood
CONN ID
C1=68 BLK
C2=68 GRY
C3=68 LT GRY
C5=02 BLK
C6=02 LT GRN
E7
E6
C3
0.8 ORN 2940
0.8 ORN 3040
B
E
C1
Battery Positive Voltage
Battery Positive Voltage
Headlamp Door Control Module
CONN ID
C1=05 BLK
C2=04 BLK
Left Headlamp Door Motor Down
Left Headlamp Door Motor Up
Right Headlamp Door Motor Up
Right Headlamp Door Motor Down
Ground
D
C1
B
A
D
C
C2
0.8 LT BLU 578
0.8 LT GRN 576
0.8 DK BLU 579
0.8 BLK 150
B
B
0.8 DK GRN 577
M
Headlamp Door Assembly – Left
M
Headlamp Door Assembly – Right
D
A
A
Ground Distribution Schematics in Wiring Systems
Splice Pack, SP100
G102